ONLINE POSITION CONTROL SYSTEM USING INCREMENTAL FUZZY CONTROL

WAN HAMIDAH BINTI WAN ABAS

A project report submitted in partial fulfillment of the requirement for the award of the Degree of Master of Electrical Engineering

Faculty of Electrical and Electronic Engineering Universiti Tun Hussein Onn Malaysia

JULY 2014

This work is dedicated to my parents *Wan Abas Bin Ngah and Hafsah binti Muhamad* For their endless love, support, encouragement and blessing iii

For my siblings and whole family for their encouragement and blessing And lastly, this report is dedicated to all those who believe in the richness of learning.

ACKNOWLEDGEMENT

Alhamdulillah and praise to Allah for His Blessing that I have finished this project successful.

First of all, I would like to express my gratitude to honorable Dr. Dirman Hanafi bin Burhannuddin, my supervisor of Master's project for his guidance, support, advices, critics and unfailing patience throughout the course of this study. He helped me a lot especially in guiding to use Matlab software. During discussion session, he gives me a lot of encouragement and assistance which finally leads me to the completion of this project.

Finally, I would like to dedicate my gratitude to my lovely parents, my family and all my friends who helped me directly or indirectly in the completion of this project. These acknowledgments would be incomplete without their support and encouragement, love and emotional supports.

Guidance, co-operation and encouragement from all people above are appreciated by me in sincere. Although I cannot repay the kindness from them, I would like to wish them to be well and happy always. Thanks a lot for everything.



ABSTRACT

In the field of fuzzy control theory, fuzzy logic controllers is one of the most active research areas and are particularly useful in controlling various types of physical processes. Therefore, this project also involved in usage of the fuzzy logic controller. Main objective of this project is to develop online position control of DC motor using Incremental Fuzzy Logic Controller (IFLC). The IFLC were developed by using MATLAB Simulink and implemented in the real position control system hardware. RAPCON platform is a hardware that was implemented in real-time session with DC motor. For simulation, signal generator used as the reference input in the form of square wave. The best gains used for the IFLC in simulation are: gain of error (GE) is 2.721, gain of change error (GCE) is 0.019 and gain of output (GCU) is 0.259. While real-time simulation use the most gains such as gain error (GE) of 1.785, gain of change error (GCE) is 0.0056955 and gain of output (GCU) is 0.01. Both method either simulation or real-time generate in 20 seconds. The result was obtained in form of graph and their performance was analysed. Based on the result, the IFLC shows the better performance of the overshoot percentage (%OS) of 0%.



ABSTRAK

Dalam bidang teori kawalan kabur, pengawal logik kabur merupakan satu bidang penyelidikan yang sangat aktif dan berguna dalam mengawal beberapa jenis proses fizikal. Oleh itu, projek ini juga termasuk dalam penggunaan pengawal logik kabur. Tujuan utama projek ini adalah untuk membina kawalan kedudukan secara talian bagi motor AT (arus terus) dengan menggunakan pengawal logik kabur tambahan (PLKT). PLKT telah dibangunkan dengan menggunakan MATLAB Simulink dan dilaksanakan dalam perkakasan sistem kawalan kedudukan sebenar. RAPCON platfom merupakan perkakasan yang digunakan dalam sesi masa-sebenar bersama motor AT. Bagi simulasi, penjana isyarat digunakan sebagai masukan rujukan dalam bentuk gelombang persegi. Gandaan yang digunakan bagi PLKT dalam simulasi adalah: ralat gandaan (GE) adalah 2.721, perubahan ralat gandaan (GCE) adalah 0.019 dan gandaan keluaran (GCU) adalah 0.259. Sementara simulasi masa-sebenar banyak menggunakan gandaan seperti ralat gandaan (GE) adalah 1.785, perubahan ralat gandaan (GCE) adalah 0.0056955 dan gandaan keluaran (GCU) adalah 0.01. Setelah simulasi dan scenario masa-sebenar telah berjaya, keputusan yang yang diperolehi adalah dalam bentuk graf dan prestasinya dianalisis. Berdasarkan kepada keputusan yang diperolehi, PLKT menunjukkan perlaksanaannya yang amat baik dengan peratus lajakan lampau maksimum (%OS) adalah 0%.



CONTENTS

	TITLI	i		
	DECL	ARATION	ii	
	DEDI	CATION	iii	
	ACKN	NOWLEDGEMENT	iv	
	ABST	RACT	v	
	CONT	TENTS	vii	
	LIST	OF TABLES	x JAH	
	LIST OF FIGURES xii			
	LIST	OF SYMBOLS AND ABBREVIATIONS	xiv	
СНАР	TER 1	INTRODUCTION	1	
	1.1	Introduction	1	
	1.2	Problem Statement	2	
	1.3	Project Objectives	2	
	1.4	Project Scope	3	
	1.5	Project Outline	3	
CHAPTER 2 LITERATURE REVIEW 4				
	2.1	Introduction	4	
	2.2	Previous Work	4	
	2.3	DC Motor Theory	6	
		2.3.1 Mathematical Equation	7	
		2.3.2 Transfer Function	8	

	2.4	Control Requirement	9
	2.5	PID Controller	10
	2.6	Incremental Fuzzy Logic	12
	CHAPTER :	3 METHODOLOGY	15
	3.1	Introduction	15
	3.2	Concept of The Project	17
	3.3	Fuzzy Logic Controller Design	17
		3.3.1 Mamdani Fuzzy Logic Control	19
		3.3.2 Fuzzy Rule Base System	20
	3.4	RAPCON Board	20
		3.4.1 Specification	21
		3.4.2 Hardware	22
		3.4.3 Software	24
	3.5	Hardware Connection	25
	3.6	DC Motor With Encoder	25
	CHAPTER 4	4 RESULT AND ANALYSIS	28
	P 4.1	Introduction	28
	4.2	DC Motor System Response	29
4.3		Incremental Fuzzy Controller Test	30
	4.4	Incremental Fuzzy Controller with RAPCON	41
		(Real-Time Experiment)	
	4.5	Discussion	51
CHAPTER 5 CONCLUSION AND RECOMMENDATION			52
	5.1	Conclusion	52
	5.2	Recommendation	53

viii

REFERENCES	54
VITA	57

ix

LIST OF TABLES

3.1	Rule Base for fuzzy controller	20
3.2	Specification of the RAPCON platform	21
3.3	Summary part of the RAPCON board functional	23
	block diagram	
3.4	The DC motor parameters	26
4.1	IFLC controller parameter values	32
4.2	Reference input values setting	32
4.3	Specifications of parameter associated with response	
	at 360°	34
4.4	Specifications of parameter associated with response	
	at 330°	34
4.5	Specifications of parameter associated with response	
	at 300°	35
4.6	Specifications of parameter associated with response	
	at 270°	36
4.7	Specifications of parameter associated with response	
	at 240°	37
4.8	Specifications of parameter associated with response	
	at 210°	37
4.9	Specifications of parameter associated with response	
	at 180°	38
4.10	Specifications of parameter associated with response	
	at 150°	39
4.11	Specifications of parameter associated with response	
	at 120°	39
4.12	Specifications of parameter associated with response	
	at 90°	40

4.13	Specifications of parameter associated with response	
	at 60°	41
4.14	IFLC controller parameter values	42
4.15	Reference input values setting	42
4.16	Specifications of parameter associated with response	
	at 360°	44
4.17	Specifications of parameter associated with response	
	at 330°	44
4.18	Specifications of parameter associated with response	
	at 300°	45
4.19	Specifications of parameter associated with response	
	at 270°	46
4.20	Specifications of parameter associated with response	
	at 240°	46
4.21	Specifications of parameter associated with response	
	at 210°	47
4.22	Specifications of parameter associated with response	
	at 180°	48
4.23	Specifications of parameter associated with response	
	at 150°	48
4.24	Specifications of parameter associated with response	
	at 120°	49
4.25	Specifications of parameter associated with response	
	at 90°	50
4.26	Specifications of parameter associated with response	
	at 60°	50

LIST OF FIGURES

2.1	Crisp PD control system 5				
2.2	Output and control signals for crisp PD control	5			
	system				
2.3	Separately excited DC motors 6				
2.4	Response specification 9				
2.5	General feedback control architecture 10				
2.6	Functional diagram of a PID Control Loop 11				
2.7	Incremental Fuzzy Controller 13				
3.1	Flow chart for develop project 16				
3.2	Block diagram of position control using IFLC system	17			
3.3	Block diagram of fuzzy controller system	18			
3.4	Fuzzy Inference System (FIS)	19			
3.5	The Input and Output of variable	19			
3.6	The functional block diagram of the RAPCON board	22			
3.7	RAPCON Board (hardware)	24			
3.8	RAPCON Software	24			
3.9	Interfacing between Personal computer and DC	25			
	Motor using RAPCON Board				
3.10	DC motor with encoder	26			
3.11	Block diagram of DC motor	27			
4.1	Hardware connection	28			
4.2	Open loop of DC motor diagram	29			
4.3	Open loop of DC motor response	29			
4.4	Close loop of DC motor diagram	30			
4.5	Close loop of DC motor response	30			
4.6	IFLC controller in subsystem form	31			
4.7	Complete design of IFLC controller system 31				



4.8	Output response at 360 degree	33
4.9	Zooming of output response at 360 degree	33
4.10	Output response at 330 degree	34
4.11	Output response at 300 degree	35
4.12	Output response at 270 degree	35
4.13	Output response at 240 degree	36
4.14	Output response at 210 degree	37
4.15	Output response at 180 degree	38
4.16	Output response at 150 degree	38
4.17	Output response at 120 degree	39
4.18	Output response at 90 degree	40
4.19	Output response at 60 degree	40
4.20	Incremental Fuzzy Logic controller for DC motor	41
	system (real-time)	
4.21	system (real-time) Output response based on IFLC at 360°	43
4.21 4.22	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360°	43 43
4.214.224.23	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330°	43 43 44
4.214.224.234.24	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300°	43 43 44 45
 4.21 4.22 4.23 4.24 4.25 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270°	43 43 44 45 45
 4.21 4.22 4.23 4.24 4.25 4.26 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270° Output response based on IFLC at 240°	43 43 44 45 45 45 46
 4.21 4.22 4.23 4.24 4.25 4.26 4.27 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270° Output response based on IFLC at 240° Output response based on IFLC at 210°	43 43 44 45 45 45 46 47
 4.21 4.22 4.23 4.24 4.25 4.26 4.27 4.28 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270° Output response based on IFLC at 240° Output response based on IFLC at 210°	43 43 44 45 45 45 46 47 47
 4.21 4.22 4.23 4.24 4.25 4.26 4.27 4.28 4.29 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270° Output response based on IFLC at 240° Output response based on IFLC at 210° Output response based on IFLC at 180° Output response based on IFLC at 180°	43 43 44 45 45 45 46 47 47 48
 4.21 4.22 4.23 4.24 4.25 4.26 4.27 4.28 4.29 4.30 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270° Output response based on IFLC at 240° Output response based on IFLC at 210° Output response based on IFLC at 180° Output response based on IFLC at 150° Output response based on IFLC at 120°	43 43 44 45 45 45 46 47 47 47 48 49
 4.21 4.22 4.23 4.24 4.25 4.26 4.27 4.28 4.29 4.30 4.31 	system (real-time) Output response based on IFLC at 360° Zooming of output response based on IFLC at 360° Output response based on IFLC at 330° Output response based on IFLC at 300° Output response based on IFLC at 270° Output response based on IFLC at 240° Output response based on IFLC at 210° Output response based on IFLC at 180° Output response based on IFLC at 150° Output response based on IFLC at 120° Output response based on IFLC at 90°	43 43 44 45 45 45 46 47 47 47 48 49 49



LIST OF SYMBOLS AND ABBREVIATIONS

DC	-	Direct Current
FIS	-	Fuzzy Interence System
FLC	-	Fuzzy Logic Controller
FPD	-	Fuzzy Proportional Derivative
GCE	-	Gain of Change Error
GE	-	Gain Error
GCU	-	Gain of Output
IFLC	-	Incremental Fuzzy Logic Controller
MATLAB	-	MATrix LABoratory
NN	-	Neural Network
OS	-	Overshoot
PD	-	Proportional-Derivative
PID	-	Proportional-Integral-Derivative
T _p		Peak Time
Tr	515	Rise Time
Ts PER		Settling Time

CHAPTER 1

INTRODUCTION

1.1 Introduction

DC motor has been widely used to improve the quality of human work, either globally or individually such as in home appliances, industrial applications, robot manipulators etc. The DC motors are choosing because it has high reliabilities, flexibilities and low costs. Most of the applications of DC motor drivers are need a position control and speed.

There are many methods used as DC motor drivers such as PID, NN, Fuzzy Logic etc. Some applications may require using only one or two actions to provide the appropriate system control.

"Proportional-Integral-Derivative (PID) controllers are commonly used for motor control applications because of their simple structures and intuitionally comprehensible control algorithms" (Manafeddin Namazov and Onur Basturk, 2010). "The PID controller has been implemented in position control system, but still suffers from poor performance because of non-linear parameters. The PID does not give satisfactory results when control parameters, loading conditions and the motor itself are changed" (Mohammad Syah Rizal, 2013).

Neural Network (NN) controllers are another method used for motor control applications. In the NN, there is abundant of architecture can be used to perform a variety types of functions. There are kind of neural network with high efficiency and strong function generalizing in terms of learning speed and simplicity of the structure. The NN need increasing the number input neural network and put some delay to the input neural network to improve performance of the network (Mohammad Syah Rizal, 2013). In this project, the fuzzy logic controller (FLC) as an intelligent controller will apply. The FLC can be designed without the exact



model of the system. Fuzzy logic is based on the principle of human expert decision making in problem solving mechanism (Dirman *et. all*, 2011).

By using the FLC, the position control performance will improve. This FLC develop will use Mamdani method. Mamdani method is widely accepted for capturing expert knowledge. Computer simulation is guided to illustrate the performance and show the result.

1.2 Problem Statements

Normally, the DC motor controller has a problem to achieve the desire position control. This problem among other is affected by the existing the nonlinearities component in the system. Moreover, these nonlinearities are often unknown and decrease the performance of position control. PID controller has been used because it most simple and easy to implement, but this type of controller still not able to improve the position control system performance because of the nonlinearities and uncertainties issues. The PID controller is not able to work well for non-linear system, and particularly complex and vague system that has no precise mathematical models. Some researchers used NN controller to improve the performance of position control, but it's still not have a good performance. To overcome these problems, the Incremental Fuzzy Control System (IFLC) is developed in this project to ensure the DC motor as a position control driver is operable in any circumstance of situations.



1.3 Project Objectives

The major objective of this research is to use the incremental fuzzy logic control to develop online position control. Its measurable objectives are as follows:

- To design the incremental fuzzy control system for position control with DC motor as a driver.
- To implement an online position control based on incremental fuzzy control system.
- 3. To test the performance of position control based on incremental fuzzy.

1.4 Project Scopes

The scopes of this project are as follows:

- a) MATLAB Simulink software is used to simulate the incremental fuzzy logic controller system developed.
- b) The controller type is an Incremental Fuzzy Logic Control system.
- c) DC motor is as a driver of the position control.
- d) The controller develop is an online.
- e) Interfacing between personal computer (pc) where the controller is build and DC motor as a plant is done by RAPCON Board.
- f) The type of layout is square wave.

1.5 Report Outline

This project deals with the proposed idea of develop a position control system for DC motor by using an Incremental Fuzzy Logic Controller (IFLC). This report is divided into five chapters. Chapter 1 is an introduction and gives an overview of the project and speaks about the scope and the main objective. Chapter 2 discusses briefly about the DC motor theory, PID controller and Incremental Fuzzy Logic Controller. Chapter 3 explained the method that was used in this project. Among the subtopics described are flow chart for develop project, flow chart for the IFLC system, IFLC design, hardware and software RAPCON, and concept of the project. Chapter 4 describes the MATLAB Simulink model for IFLC system of position control. It also shows the result of simulation and real-time experiment. And the last chapter is Chapter 5. This chapter is about the conclusion and the future scope of the designed controller.

CHAPTER 2

LITERATURE REVIEW

2.1 Introduction

This chapter will discuss the previous studies that have been accomplished by other researchers in same area. There are many researchers who have been implemented fuzzy logic control on the position control with DC motor as a driver. Related to this JUNCES project title, the review focused on the incremental fuzzy control system resources like journal, proceeding thesis and also book.

2.2 **Previous Works**



There are many papers have been published about fuzzy control system design for DC motor (Manafeddin Namazov and Onur Basturk, 2010). The comparison between Proportional-Integral-Derivative (PID) and Fuzzy Logic Controller (FLC) application for position control has been done (Paul et.all., 1994) and the result shows the FLC performed better than PID. Other work, based on Neural Network controller. The results are obtained from the simulation and real-time experiment. From the result, neural network controller has been given the best controller for position control with DC motor as driver. The neural network controller satisfies all the specifications underlined better than PID controller. The neural network controller provides faster response and more precise control compared to PID controller (Muhamad Syah Rizal, 2013).

Figure 2.1 shows the PD control system designed in MATLAB Simulink where controller coefficients are adjusted using the Signal Constraint blocks. Integral

coefficient of PID controller is set to zero (i.e K = 0) (Manafeddin Namazov and Onur Basturk, 2010).



Figure 2.1: Crisp PD control system

FLCs are complex, nonlinear controllers. Therefore it's difficult to predict how the rise time, settling time or steady state error is affected when controller parameters or control rules are changed. On the contrary, PID controllers are simple, linear controllers which consist of linear combinations of three signals (Manafeddin Namazov and Onur Basturk, 2010).



Figure 2.2: Output and control signals for crisp PD control system

Figure 2.2 shows output and control signals of PD control system with adjusted parameters.

Ankur Gupta et.all. (2011) has been presented the position control of servo motor in three difference schemes. They are PID, Fuzzy and sliding mode Fuzzy Control. Each of them is discussed in term of the normal case, parameter variation case, and disturbance. The results show that PID is effective for a constant reference input but is ineffective for parameter variation and disturbance cases. Then Fuzzy controller gives better performance compared to PID controller but results are ineffective for disturbance case. While sliding mode fuzzy control shows that the system performance improvement when compared to PID and fuzzy control for parameter variation case and for disturbance case. So sliding mode fuzzy control is better in terms of control performance compared with other controllers.

2.3 DC Motor Theory

In armature control of separately excited DC motors, the voltage applied to the armature of the motor is adjusted without changing the voltage applied to the field. Figure 2.3 describes a separately excited DC motor equivalent model (Norman S. Nise, 1995).



Figure 2.3: Separately excited DC motors

Where:

- J Moment of Inertia of the motor (kg m2)
- B Friction coefficient of the motor (Nm/rad/sec)
- K_e Torque constant of the motor (Nm/A)

- $K_b\;$ Motor back emf constant (V/rad/sec)
- Armature current (A) ia
- V_a Armature voltage applied (V)
- R_a Armature resistance (ohms)
- L_a Armature inductance (mH)

2.3.1 **Mathematical Equation**

Voltage equation of the armature circuit under transient is given by

$$v(t) = R_a i_a(t) + L_a \frac{di_a(t)}{dt} + K_s \Phi \omega_m(t)$$
(2.1)

From the dynamics of motor load system

$$J\frac{d\omega_m(t)}{dt} = T(t) - T_L(t) - B\omega_m(t)$$

Further

he dynamics of motor load system

$$J\frac{d\omega_{m}(t)}{dt} = T(t) - T_{L}(t) - B\omega_{m}(t) \qquad (2.2)$$

$$T = K_{e} \Phi i_{a}(t) \qquad (2.3)$$

When field current is kept constant, flux remains constant. Replacing $K_e \phi$ by a constant K_e , yields

$$v(t) = R_a i_a(t) + L_a \frac{di_a(t)}{dt} + K_e \omega_m(t)$$
(2.4)

$$J\frac{d\omega_m(t)}{dt} = K_b i_a(t) - B\omega_m(t) - T_L(t)$$
(2.5)

$$K_b i_a(t) = J \frac{d\omega_m(t)}{dt} + B\omega_m(t)$$
(2.6)

2.3.2 Transfer Function

Laplace transforms of Eq. (2.1) to Eq. (2.5) are:

$$V(s) = R_a I_a(s) + L_a I_a(s) \cdot s + K_e W(s)$$
(2.7)

$$K_b I_a(s) = J_m W(s) \cdot s + B_m W(s)$$
(2.8)

$$I_{a}(s) = \frac{J_{m}W(s).s + B_{m}W(s)}{K_{b}}$$
(2.9)

$$I_a(s) = \frac{W(s)}{K} [J_m \cdot s + B_m]$$
(2.10)

Substitute Eq. (2.9) into Eq. (2.6):

$$V(s) = R_{a} \left(\frac{W(s)}{K_{e}} [J_{m} \cdot s + B_{m}] \right) + L_{a} \cdot s \cdot \left(\frac{W(s)}{K_{e}} [J_{m} \cdot s + B_{m}] \right) + K_{b} W(s) (2.11)$$

$$V(s) = \left(\frac{W(s)}{K_{e}} [J_{m} \cdot s + B_{m}] \right) [R_{a} + L_{a} \cdot s + \frac{K_{b} K_{e}}{J_{m} \cdot s + B_{m}}]$$
(2.12)
$$V(s) = W(s) \frac{1}{K_{e}} [L_{a} \cdot J_{m} \cdot s^{2} + (R_{a} J_{m} + L_{a} B_{m}) \cdot s + (R_{a} B_{m} + K_{b} K_{e})]$$
(2.13)



$$\frac{W(s)}{V(s)} = \frac{K_{e}}{L_{a}J_{m}s^{2} + (R_{a}J_{m} + L_{a}B_{m})s + (R_{a}B_{m} + K_{b}K_{e})}$$
(2.14)

The relation between position and speed is:

$$\theta(s) = \frac{1}{2}W(s) \tag{2.15}$$

Then the transfers function between shaft position and armature voltage without load is:

$$\frac{\theta(s)}{V(s)} = \frac{K_{\varepsilon}}{L_a J_m \cdot s^3 + (R_a J_m + L_a B_m) \cdot s^2 + (R_a B_m + K_b K_{\varepsilon}) \cdot s}$$
(2.16)

2.4 Control Requirement

The controller requirements are analyzed based on its output response parameters. It will indicate the performance of the controller. The parameters are given below (Norman S. Nise, 1995).



Figure 2.4: Response specification

(i) Rise time, T_r

The time required for the response to progress from 0.1 to 0.9 of the final value.

(ii) Peak time, T_p

The time required to reach the first or maximum peak.

(iii) Settling time, T_s

The time required for the response taken to fall within and stay within $\pm 2\%$ of the steady-state value.

(iv) Percent overshoot, %OS

The maximum amount limits for the response to overshoots the steady-state, or final value at the peak time. The percentage overshoot is expressed as in Equation (2.16)

$$\%OS = \frac{c_{\max} - c_{final}}{c_{final}} \times 100$$
(2.16)

2.5 PID controller

PID stands for Proportional-Integral-Derivative. This is a type of feedback controller whose output, a control variable (CV), is generally based on the error between some user-defined set point (SP) and some measured process variable (PV). Each element of the PID controller refers to a particular action taken on the error.

There are many situations that require some type of position control system. This section reviews the fundamental of PID controllers and presents detailed simulations or design for development of digital servomotor controller. PID controllers are commonly used to regulate the time-domain behavior of many different types of dynamic plants. These controllers are extremely popular because they can usually provide good closed loop response characteristics, can be tuned using relatively simple rules and are easy to construct using either analogue or digital components. Consider the feedback system shown in Figure 2.5 where assume that the plan is a DC motor whose shaft position must be accurately regulated.



Figure 2.5: General feedback control architecture

The PID controller algorithm involves three separate constant parameters that is the proportional (P), the integral (I) and derivative (D) values. These values can be interpreted in terms of time where P depends on the *present* error, I on the accumulation of *past* errors, and D is a prediction of *future* errors, based on current rate of change. The weighted sum of these three actions is used to adjust the process via a control element such as the position of a control valve, a damper, or the power supplied to a heating element.

By tuning the three parameters in the PID controller algorithm, the controller can provide control action designed for specific process requirements. The response of the controller can be described in terms of the responsiveness of the controller to an error, the degree to which the controller overshoots the setpoint, and the degree of system oscillation. Note that the use of the PID algorithm for control does not guarantee optimal control of the system or system stability.

Some applications may require using only one or two actions to provide the appropriate system control. This is achieved by setting the other parameters to zero. A PID controller will be called a PI, PD, P or I controller in the absence of the respective control actions. PI controllers are fairly common, since derivative action is sensitive to measurement noise, whereas the absence of an integral term may prevent the system from reaching its target value due to the control action.



Figure 2.6: Functional diagram of a PID Control Loop

REFERENCES

- Aamir, Muhammad. (2013). On Replacing PID controller with ANN controller for DC motor position control. International Journal of Research Studies in Computing. pp. 21-29.
- Ankur Gupta, Aziz Ahmad and Amit Kumar.(2011). Position Control Of Servo Motor Using Sliding Mode Fuzzy Controller. International Journal Of Advances In Engineering& Technology.pp. 118-127.
- Brahoumi EM and Ben salah B. (2011). New Positioning Control of Stepper Motor using BP Neural Networks. Journal of Emerging Trends in Computing and Information Sciences. pp 300-306.
- C. Ganesh, B. Abhi, V.P.Anand, S.Aravind, R.Nandhini and S.K. Patnaik. (2012). DC Position Control System – Dertermination Of Parameters and Significance on System Dynamics. ACEEE Int. J. On Electrical and Power Engineering. pp. 1-5.
- C. S. Lee and R.V. Gonzalez. (2008). *Fuzzy logic versus a PID controller for position control of a muscle-like actuated arm*. Journal of Mechanical Science and Technology. pp 1475-1482.
- D.F.Ahmed, S.K.H. Al Dawery and H.A.O Al-Anbari. (2007). On-Line Control Of The Nuetralization Process Based On Fuzzy Logic. Emirates Journal for Engineering Researh. pp.89-97.
- Dirman Hanafi, Mohd Nor Mohd Than, Abdulrahman A.A. Emhemed, Tatang Mulyana, Amran Mohd Zaid, Ayob Hj. Johari. (2011). *Heat Exchanger's Shell* and Tube Modeling for Intelligent Control Design. IEEE. 978-1-61284-486-2/11/\$26.00.pp.37-41
- Gang Feng (2006). A Survey on Analysis and Design of Model Based Fuzzy Control Systems. IEEE Transactions on Fuzzy Systems. pp 676-697.

- Gopal K. Dubey. *Fundamental Of Electrical Drives* second edition. Alpha Science International Ltd. pp.70-97.
- Husain Ahmed, Dr. Gagan Singh, Vikash Bhardwaj, Saket Saurav and Shubham Agarwal. (2013). *Controlling of DC Motor using Fuzzy Logic Controller*. Conference on Advances in Communication and Control Systems 2013. pp. 666-670.
- Jantzen, Jan. (2007). Foundations of Fuzzy Control. England: John Wiley & Sons Ltd.
- K. Prema, N. Senthil Kumar and SubransuSekhar Dash. (2013). Online Control of DC Motors using Fuzzy logic Controller for Remote Operated Robots. J Electr Eng technol Vol.8. pp. 742-752.
- Manafeddin Namazov and Onur Basturk. (2010). DC Motor Position Control Using Fuzzy Proportional-Derivative Controlles with different Defuzzification Methods. Turkish Journal Of Fuzzy Systems. pp.36-54.
- Mohamad Syah Rizal Bin Abdullah, (2013) Neural Network Controller For Improvement Of Position Control System. Universiti Teknologi Tun Hussein Onn.
- Mohd Fua'ad Rahmat and Mariam Md Ghazaly.(2006). Performance Comparison Between PID And Fuzzy Logic Controller In Position Control System Of DC Servomotor.Jurnal Teknologi.Universiti Teknology Malaysia. pp.1-17.
- Norman S. Nise. (1995). *Control System Engineering*. 2nd. ed. Addison-Wesley Publishing Company, Canada. ISBN 0-8053-5424-7
- Otman. M. Ahtiwash, Mohd Z. Abdulmuin and Siti Fatimah Siraj.(2002). A Neural-Fuzzy logic Approach for Modeling and Control of Nonlinear Systems. International Symposium on Intelligent Control. pp. 270-275.
- Oyas Wahyunggoro and Nordin Saad.(2010). *Development of Fuzzy-logic-based Self Tuning PI Controller for Servomotor*. Advanced Stategies for Robot Manipulators. S. Ehsan Shafiei (Ed.), ISBN: 978-953-307-099-5. InTech, Available from: http://www.intechopen.com/books/advanced-strategies-forrobotmanipulators/development-of-fuzzy-logic-based-self-tuning-pi-controllerfor-servomotor
- P. Brandstetter, R. Hrbac, M.Polak and L. Stepanec. Application Of Fuzzy Logic In Control Of Switched Reluctance Motor. Advances in Electrical and Electronic Engineering. pp 68-71.

- Paul I-Hai Lin, Santai Hwang and John Chou. (1994). Comparison On Fuzzy Logic And PID Controls For A DC Motor Position Controller. Conference Record of the 1994 IEEE Industry Aplications Society Annual Meeting. pp 1930-1935.
- Pooya Hajebi and Seyed Mohammad Taghi AlModarresi. (2012). Online Adaptive Fuzzy Logic Controller Using Neural Network for Networked Control Sytems. ICACT 2012. ISBN 978-5519-163-9. pp. 888-893.
- Ritu Soni, DBV Singh, Pramod Pandey and Priyanka Sharma. (2013). Simulation of Optimal Speed Control for a DC Motor Using Conventional PID Controller and Fuzzy Logic Controller. International Journal of Information and Computation Technology. pp. 181-188.
- The Math Work: Fuzzy Logic Toolbox for use with MATLAB.
- U.A. Bakshi and V.U.Bakshi. (2011). *Control System Engineering*. Techical Publications, India. ISBN 978-81-8431-463-2.
- Zeltom LLC. RAPCON: Real-time Rapid Control Prototyping Platform for Matlab/Simulink. Retrieved on December 26, 2013, from http://zeltom.com/products/rapcon
- Zeltom LLC. DC Motor System User Manual 1.3. Retrieved on December 26, 2013, from http://zeltom.com/documents/dcms_um_13.pdf

